



**Part Number:** EFS-0432115-040

Revision 20160816 - Generated 2016-Aug-16



<b>A</b>	42.8 ± 0.64 mm	1.685 ± 0.025 in
<b>B</b>	21.1 ± 0.33 mm	0.831 ± 0.013 in
<b>C</b>	15.4 ± 0.25 mm	0.606 ± 0.010 in
<b>D</b>	15 mm (min.)	0.591 in (min.)
<b>E</b>	30.4 mm (min.)	1.197 in (min.)
<b>F</b>	11.9 ± 0.25 mm	0.469 ± 0.010 in
<b>Mass</b>	(approximate)	56 grams/half
<b>Magnetic Dimensions</b>	A <sub>e</sub> - Eff. Mag. Cross Section	1.83 cm <sup>2</sup>
	L <sub>e</sub> - Eff. Mag. Path Length	9.84 cm
	V <sub>e</sub> - Eff. Core Volume	18.0 cm <sup>3</sup>
	WA - Min. Eff. Window Area	2.74 cm <sup>2</sup>
	sa - Surface Area	73.5 cm <sup>2</sup>
mlt - mean length per turn	9.16 cm	
<b>Inductance</b>	μ <sub>i</sub> (reference)	40
	A <sub>L</sub> value (nominal)	108 nH/N <sup>2</sup>
	Test Winding	N=100, #18 AWG
	Frequency	10 kHz
	Voltage on Agilent 4284A	0.81 V
A <sub>L</sub> tolerance	±8%	
<b>Core Loss</b>	$\text{Core Loss (mW/cm}^3\text{)} = \frac{f}{\frac{a}{B_{pk}^3} + \frac{b}{B_{pk}^{2.3}} + \frac{c}{B_{pk}^{1.65}}} + d \cdot B_{pk}^2 \cdot f^2$	
	where B <sub>pk</sub> expressed in gauss, f expressed in hertz, and: a=1.00E+06, b=2.70E+08, c=3.23E+06, d=7.09E-14	
	B <sub>pk</sub>	1000 G
	frequency	50 kHz
	Core Loss (nominal)	889 mW/cm <sup>3</sup>
Core Loss (maximum)	1,022 mW/cm <sup>3</sup>	
<b>DC Saturation</b>	$\% \mu_i = \frac{1}{a + b \cdot H^c} + d$	
	where H expressed in oersteds, and: a=0.01, b=1.93E-06, c=1.62, d=19.99	
	H <sub>DC</sub>	100 Oe
	Percent Initial Perm(nom.)	83.3%
Percent Initial Perm(min.)	79.0%	
<b>Coating/Pkg</b>	Coating Type:	None
	Voltage Breakdown (min.)	N/A
	Limit	N/A
	Package Quantity	175 Halves/Box

<b>Winding Table</b>	<b>Wire Size</b>	AWG	8	10	12	14	16	18	20	22	24	26	28
		mm	3.150	2.500	2.000	1.600	1.250	1.000	0.800	0.630	0.500	0.400	0.315
	<b>Full Winding</b>	Turns	15	23	35	55	85	131	203	314	486	752	1,164
	Rdc(Ω)	2.8 m	6.9 m	16.7 m	41.7 m	102.4 m	251.0 m	618.7 m	1.5	3.7	9.2	22.7	

